

Red Fire Telephone Outstation c/w Handset (push to open)

Part No. **EVC301RPO**



Overview

An attractive Type A fire telephone outstation c/w telephone-style handset.

Supplied in a durable 'push-to-open' red steel case.

Ideal for use in fire telephone and stadium marshalling applications.

Allows stewards and fire marshals to communicate with a SigTEL Master Controller (and vice versa).

Facilitates reliable two-way communication in a fire emergency between a permanently manned control room and key points of a site.

True duplex speech.

Can be surface mounted using a T-BEZ302 bezel.

Meets and exceeds the requirements of BS 5839-9 when correctly installed.

Technical Specifications

Approvals/certifications	Facilitates compliance with BS5839-9 when correctly installed.
Supply/operating voltage	11V DC derived from a compatible SigTEL Master Controller (drops to 6 V DC when in use).
Quiescent current	1mA
Activation current	25mA (current draw when handset is in use).
Open collector outputs	None.
Indicators	When the operator in the control room calls the outstation, a pulsed ringing tone sounds at the outstation.
Controls	'Push to Open' catch. Telephone-style handset (lift to answer or make a call).
Expansion connections	None.
Product dimensions (mm)	202 W x 278 H x 100 D mm.
Construction & finish	Red steel (RAL 3000).
IP Rating	IP20.



Weight	3 kg.
Operating conditions/temperature	-5°C to +40°C. Max relative humidity: 95%.
Notes	Microphone frequency response 250 Hz to 5 kHz ± 3 dB; Loudspeaker frequency response 250 Hz to 4 kHz ± 3 dB.



T 01942 322744 E sales@c-tec.co.uk
F 01942 829867 W www.c-tec.com



C-TEC, Challenge Way, Martland Park, Wigan, WN5 0LD United Kingdom