

AJAX

STREETSIREN



Wireless outdoor siren that notifies of danger using sound and light. The device is installed outside the room to raise an alarm for everyone to hear.



Ready to operate straight out the box: the battery is already installed, therefore there is no need to disassemble the siren. With one click, it can be connected to the hub in the mobile application. It can be mounted on the SmartBracket in just a few minutes.



Specification

Classification	Light and sound radio channel security sounder
Type of siren	Wireless
Installation method	Indoors /Outdoors
Compatibility	Operates only with Hub, Hub Plus and ReX
Type of notification	Sound/light
Sound volume level	Adjustable, 81-113 dB at a distance of 1 m
Alarm length	Adjustable, 3-180 s
Indication of armed/ disarmed status	Yes
Alarm signal delivery time	0,15 s
Power supply	Battery: Four CR123A batteries Power supply voltage: 3 V Battery life — up to 5 years Mains supply: DC 12 V±20%
Jeweller radio technology	Communication range with central unit — up to 1,500 m in an open space Two-way communication between devices Operating frequencies — 868.0-868.6 MHz Self-adjusting RF output power — up to 25 mW Block encryption based on AES algorithm Device polling period — 12-300 s
Temperature sensor	Available
Operating temp range	From -25° C to +50° C
Permissible humidity	Up to 95%
Protection class of body	IP54
Anti-sabotage	Protection against fraud Jamming detection Tamper-resistant
Remote setting and testing	+
Dimensions	200x200x51mm
Weight	528 g
Certification	Grade 2, CE
Complete set	StreetSiren siren SmartBracket mounting panel 4 batteries CR123A (pre-installed) Installation set User's guide