

Isolating Base



Product overview

Product Type	Isolating Base
Part No.	45681-284
Digital communication	XP95, Discovery and CoreProtocol® compatible

Compliance



Product information

The Isolating Base senses and isolates short circuit faults on system loops and spurs.

The base is loop-powered, polarity sensitive and accepts the XPERT card to set the address of the associated device.

In short-circuit conditions the integral yellow LED is illuminated. The detector associated with the base remains active under short-circuit conditions. Power and signals to the affected section are restored automatically when the fault is cleared.

Operation

Under normal operating conditions a low impedance is present between the -IN and -OUT terminals of the base so that power and signals pass to the next base in line.

If a short-circuit or abnormally low impedance occurs the fall in voltage is sensed and the base isolates the negative supply in the direction of the fault. The isolated section is tested using a current pulse every five seconds. When the short-circuit is removed, the power will automatically be restored.

If it is a requirement that no device is lost in the event of a single short-circuit fault every non-isolated detector should be fitted to an isolating base.

Technical data

All data is supplied subject to change without notice. Specifications are typical at 24 V, 25 °C and 50% RH unless otherwise stated.

Supply Voltage	17 V -28 V dc plus 9 V dc protocol pulses
Isolation indicator	Yellow LED, lit continuously in isolation condition
Current consumption	
at 18 V dc	23 µA
at 28 V dc	43 µA
at 18 V dc and adjacent sector isolated	4 mA
Maximum line current	
non-isolating continuous	1.0 A
transition into isolation	3.0 A
Operating temperature	-20°C to +60°C
Storage temperature	-30°C to +80°C
Humidity (no condensing or icing)	0% to 95% relative humidity
Approved use	Indoor use only
Standards and approvals	CPR, LPCB, VdS, FG, CCMG
Dimensions	100 mm diameter x 24 mm height
Weight	100 g
Materials	
Body	White polycarbonate moulding
Terminals	Nickel plated stainless steel

Note: for further information on the isolator, refer to PP2090 -Short-circuit Isolation available from www.apollo-fire.co.uk

In applications where it is not necessary to use an isolating base for each detector, up to twenty detectors or equivalent surge current may be installed between isolating bases.

EMC Directive 2014/30/EU

The Isolating Base complies with the essential requirements of the EMC Directive 2014/30/EU, provided that it is used as described in this data sheet.

A copy of the Declaration of Conformity is available from Apollo on request.

Conformity of the Isolating Base with the EMC Directive, does not confer compliance with the directive on any apparatus or systems connected to it.

Construction Products Regulation 305/2011/EU

The Isolating Base complies with the essential requirements of the Construction Products Regulation 305/2011/EU.

A copy of the Declaration of Performance is available from Apollo on request.

This page has intentionally been left blank