	DATASHEET	
	30 radio zone control panel, expands up	
	to 60 zones using wired and wireless	
	expanders, Grade 2, Eaton	
I-ON30RKIT-WKP	Secureconnect enabled, built in	
	Ethernet, includes: three pet tolerant	
	PIRs, one slim-line door contact, five	
	prox tags, wired keypad	
General specifications	Product Name	Eaton i-on30R burglar alarm kit
·	Catalog Number	I-ON30RKIT-WKP
	EAN	5060096855774
	Product Length/Depth	430 mm
	Product Height	125 mm
	Product Width	
	Product Weight	2.68 kg
	Compliances	CE marking
	Certifications	
Product specifications	Occurrence memory	Yes
·	On Board Outputs (Panel)	1
	Out of the box radio zones	30
	Web browser interface	
	On Board Outputs (Plug By)	0
	VdS Class	None
	Users	
	With power adaptor	No
	Wired internal sounders	
	Supports ARD	
	Back-up battery size - max	7Ah
	Radio connection	
	Communications options	On Board Ethernet. Plug on GSM, PSTN
	Log events	1000
	Number of outputs for optical signal	
	generators	2
	Number of keypads	20
	Number of bus devices	
	Integrated dial device	
	Number of sabotage groups	31
	Emergency power supply integrated	
	EN 50131 Security Grade	
	Connection	Hybrid
	Out of the box wired zones	
	Cloud support	
	Wired external sounders	
	Total capacity zones	60
	Number of indicator groups	

Operating voltage	230 V
Custom outputs	4
Power supply size	1A
Back-up battery quantity	
Radio internal sounders	
Shunt groups	
Suitable for bus connection	
Radio external sounders	