	DATASHEET	
	868.6625 MHz Two channel radio	
762REUR-00	receiver	
General specifications	Product Name	Eaton telemetry receiver
,	Catalog Number	762REUR-00
	EAN	5060096851493
	Product Length/Depth	35 mm
	Product Height	185 mm
	Product Width	130 mm
	Product Weight	.57 kg
	Compliances	CE marking
	Certifications	
Product specifications	Operating humidity - max	95 %
-	Transmission power	10
	Compliance	EN 50130-4:2011+A1:2014, EN 60950-1:2006+A2:2013, EN 300 220-2 V2.4.1, EN 301 489-1 V1.9.2, EN 301 489-3 V1.6.1
	Operating temperature - min	-10 °C
	Current	Other
	Suitable for venetian/roller shutter switch	No
	Rolling code system	
	Surface finish	Matt
	Mounting Method	Wall-mount Surface mounted (plaster)
	Devices per channel	4
	Internal aerial	Yes
	Suitable for pulse button	
	Channels	2
	Material quality	Thermoplastic
	Printed circuit board/module	
	Ral-Number (Akin)	0
	Push button mode	
	Radio frequency	868.6625 Mega Hertz
	Power consumption	55 mA
	Modulation	FM
	Operating temperature - max	55 °C
	Programming display	
	Suitable for roller shutter switch	
	Replacement battery code	Not applicable
	With radio controlled push button	
	Degree of protection	NEMA Other IP Other

Enclosure Colour Code length (bit) Radio coding device Device type In tube base housing Suitable for switch Suitable for dimmer Alarm outputs Enclosure material Halogen Free Type of fastening Transparent Surface protection Current supply Switching mode In housing Number of commands Manual radio transmitter	T	T
Radio coding device Device type Radio receiver In tube base housing Suitable for switch Suitable for dimmer Alarm outputs Enclosure material Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply Switching mode In housing Number of commands	Enclosure Colour	White
Device type In tube base housing Suitable for switch Suitable for dimmer Alarm outputs Enclosure material Halogen Free Type of fastening Transparent Surface protection Current supply Switching mode In housing Number of commands	Code length (bit)	16
In tube base housing Suitable for switch Suitable for dimmer Alarm outputs Enclosure material Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply Switching mode In housing Number of commands	Radio coding device	
Suitable for switch Suitable for dimmer Alarm outputs 2 relay contacts Enclosure material Plastic Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Device type	Radio receiver
Suitable for dimmer Alarm outputs 2 relay contacts Enclosure material Plastic Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	In tube base housing	
Alarm outputs Enclosure material Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply Switching mode In housing Number of commands	Suitable for switch	
Enclosure material Plastic Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Suitable for dimmer	
Halogen Free Type of fastening Mounting with screw Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Alarm outputs	2 relay contacts
Type of fastening Mounting with screw Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Enclosure material	Plastic
Transparent Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Halogen Free	
Surface protection Current supply 25 VDC Switching mode In housing Number of commands	Type of fastening	Mounting with screw
Current supply 25 VDC Switching mode In housing Number of commands	Transparent	
Switching mode In housing Number of commands	Surface protection	
In housing Number of commands	Current supply	25 VDC
Number of commands	Switching mode	
	In housing	
Manual radio transmitter	Number of commands	
	 Manual radio transmitter	
LED indicator 8	LED indicator	8
Suitable for venetian shutter	Suitable for venetian shutter	
switch	switch	